

## APEX CLOUDPOWER UPDATE INSTRUCTIONS



### Updating to firmware 1.3.4

**⚠ Important:** All amplifiers **must** be running firmware 1.3.3 **before** updating to firmware 1.3.4.

CloudPower firmware updates can be done conveniently through the IntelliCloud web interface. Please note that you need to restart the amplifier manually to complete the process.

#### To update the firmware:

You are advised to make backups of amplifier global presets and speaker presets before starting a firmware update. See the user guide for details of how to download presets.

1. If multiple amplifiers are employed in a network, remove all amplifiers from the network before beginning the firmware update. Each amplifier must be updated individually.
2. If the amplifier is running any version of firmware older than 1.3.3, it **must** first be updated to 1.3.3 before making the upgrade to 1.3.4, completing steps 4 to 8 of the update process for both 1.3.3 and 1.3.4. You can check the current firmware version on the Settings / About screen in IntelliCloud.
3. Download the firmware **zip file/s** you require from [www.apex-audio.be/downloads](http://www.apex-audio.be/downloads)
4. Select the required file using the **Select File** button.



5. Click **Update Now**.
6. The front panel OLED display will show the **update progress**. Do not turn the power off during the update. Once completed, the message "**Please Restart**" will appear on the display.
7. Turn the amplifier off and back on to complete the process.
8. After a firmware update, it is advised to clear your browser cache if you have been using a previous version of the IntelliCloud software on the same device. This will ensure that the interface is displayed correctly.

The **About** menu will present the device's model, serial number, MAC address, and current firmware version. You can also download the latest manual from this section.